truvami

tag L



80 x 54 x 23 mm

LoRaWAN® GNSS Wi Fi Sniffing BLE Scanning

Truvami® tag L is a powerful and robust GNSS tracking device that integrates a multistandard GNSS receiver, passive Wi-Fi MAC address scanner, Bluetooth 5.2 connectivity, and an accelerometer into a compact design. It offers seamless indoor-outdoor tracking by combining satellite communication and scanning nearby Wi-Fi Access Points, while its highly configurable firmware allows for fine-grained adaptation to specific use cases, optimizing performance and battery lifetime.

Multi-protocol approach

Accurate indoor and outdoor positioning through WiFi, BLE and GNSS technology

High accuracy

Achieves very high accuracy in location monitoring

Flexible charging

Rechargeable batteries with both wireless and usb type-c cable options

Built-in accelerometer

Features an integrated accelerometer to trigger motion-induced location fixes

High durability

The durable housing prepares the device for operation in harsh environments

Compact size

Designed for the smallest requirements

Datasheet 2024 version 1.0

Copyright © Truvami 2024. All Rights Reserved. | www.truvami.com

Mechanics & power

Mechanical specifications

Weight	103g
Dimensions	80 x 54 x 23 mm
Enclosure	Nylon

Operating conditions

Temperature	0 - 60 °C
Humidity	0 – 95 % RH, non-condensing

Power management

Battery type	Lithium polymer
Power	3.7V, 0.85 Ah
Charging	USB-C

Estimated battery life*

*LiPo self-discharging is not calculated in

1 position / day	2 years
1 position / hour	6 months
1 position / 5 min.	20 days

Communication

LoRaWAN frequencies

EU868 MHz

US915 MHz – on request

AU915 MHz – on request

LoRaWAN details

LoRaWAN® device type	Class A
LoRaWAN® version	LoRaWAN® 1.0.3
Supported LoRaWAN® features	OTAA, ADR, adaptive channel setup
LoRaWAN® receiver sensitivity	-127 dBm (SF7, 125 kHz) to -141 dBm (SF12, 125 kHz)
LoRaWAN® transmission power	14 dBm / 22 dBm (depending on region)

Location

GNSS

Receiver	U-Blox M10 GNSS receiver
GNSS	BeiDou, Galileo, GLONASS, GPS / QZSS
GNSS bands	L1
Accuracy (assuming - 130 dBm)	3-5m

WiFi

Receiver	2.4 GHz passive MAC scanning 802.11 b/g/n
Frequency band	2412 – 2484 MHz
Sniffer sensitivity (best-case)	-75 dBm
Accuracy	10 - 20 meters

BLE

Transceiver	Advertising, FOTA, device config via BLE connection, 2.4 GHz passive BLE beacon scanning capabilities
Transmission power	6 dBm
Sensitivity	-106.7 dBm(125 kbps) to -96.2 dBm(2 Mbit/s)
Accuracy	Depends on infrastructure

Sensors and peripherals

Accelerometer (3-axis)

Range	±2, ±4, ±8, ±16
Resolution	16 bit
Accuracy (typ.)	±20 mg

Integration and security

Truvami application

The truvami's application offers a range of powerful features, including receiving, decoding, storage, and efficient accessibility of the data for further processing. With the option of on-premise or cloud service installation, the application provides flexible deployment options to suit your needs. The application is built on a scalable and highly available architecture, allowing for independent scaling of microservices. When deployed on-premises, it can be horizontally and vertically scaled to meet the demands of your IoT solution.

Third party integration

SSO: Bring your own identity provider to truvami. We support SAML 2.0 and OpenID Connect.
API: Integrate truvami with your existing systems. We provide a RESTful API for easy integration.

Data security

LoRaWAN: Securely connect your LoRaWAN devices to truvami. LoRaWAN® networks use AES-128 Encryption.
TLS: Securely connect your devices to truvami.

Device management

Configure device parameters such as position update rate, movement and accelerometer settings, and more to fit any tracking application. The firmware can be upgraded with Bluetooth, while the settings can be configured via LoRaWAN downlink.

Operating modes

Efficiency mode	Settings optimized for battery saving
Dynamic mode	Regular interval for real-time tracking
Custom	Configure the parameters yourself to fit your needs

Customization

Branding	Customize the look and feel of truvami to match your corporate identity.
Custom views	Create custom views to display the data in a way that suits your needs.
Bring your own map	Use your own map provider in truvami

Disclaimer

We reserve the right to make technical changes, which serve to improve the product, without prior notification.
LoRa®, Semtech®, the Semtech logo, LoRa®, and LoRaWAN® are registered trademarks or service marks of Semtech Corporation, the LoRaAlliance® or its affiliates.
SAFETY-CRITICAL, MILITARY, AND AUTOMOTIVE APPLICATIONS DISCLAIMER: Truvami products are not designed for and will not be used in connection with any applications where the failure of such products would reasonably be expected to result in significant personal injury or death ("Safety-Critical Applications") without an truvami officer's specific written consent. Safety-Critical applications include, without limitation, life support devices and systems, equipment, or systems for the operation of nuclear facilities and weapons systems. Truvami products are not designed nor intended for use in military or aerospace applications or environments. Truvami products are not designed nor intended for use in automotive applications unless specifically designated by Truvami as automotive grade.

truvami

Truvami® is an IoT startup specialized in flexible end-to-end tracking solutions, based in Zurich, Switzerland. Our mission is to support enterprises in safeguarding their workforce and valuable assets through cutting-edge tracking technologies at smallest size. truvami offers a portfolio of different trackers that are designed to serve different use-cases in vertical markets like transport, logistics, industrial, construction, fleet- and animal tracking. The innovative multi-protocol approach combined with a dedicated geolocation engine allows seamless in- and outdoor tracking. Together with Truvami's cloud software platform, customers can easily integrate the solution into their existing IT landscape.

Get in touch today!

truvami.com



Copyright © truvami 2024. All Rights Reserved.
www.truvami.com